

GUJARAT TECHNOLOGICAL UNIVERSITY
BE - SEMESTER-VI • EXAMINATION – SUMMER • 2014

Subject Code: 160706

Date: 30-05-2014

Subject Name: System Programming

Time: 10:30 am - 01:00 pm

Total Marks: 70

Instructions:

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

- Q.1**
- (a) 1. List and explain various types of grammar. **04**
2. Compare Problem oriented and Procedure oriented languages **03**
- (b) Given following expression = - (a+b) *(c+d) + (a+b+c) **07**
1. Draw a Syntax tree for the expression
2. Write a three-address code for the expression
3. Give triple representation for the three address code of the expression
- Q.2**
- (a) Perform lexical, syntax and semantic analysis on below C statement **07**
 $a = b + c * d * 100 + e / f$
Where data type of b, c & e are integers and remaining all variables are float.
- (b) Define Simple Phrase and Handle. Using Handle and Simple Phrase trace the bottom up parsing algorithm. **07**
Grammar is :
$$E \rightarrow T + E \mid T - E \mid T$$
$$T \rightarrow T * V \mid T / V \mid V$$
$$V \rightarrow a \mid b \mid c \mid d$$

String is : a - b * c + d
- OR**
- (b) When Left- factoring on a grammar is applied? Apply left- factoring on the below given grammar and perform Predictive Parsing. **07**
Grammar is
$$S \rightarrow i E t S \mid i E t S e S \mid a$$
$$E \rightarrow b$$

String is : i b t a e i b t a
- Q.3**
- (a) Write general purpose macro to move the contents of one area of memory into another area of memory. Assume that destination area is larger in size, remaining part of it should be padded with zeroes at the end of the area. **07**
- (b) Explain use and field of following tables of a macro **07**
KPDTAB, MDT, EVTAB, SSTAB
- OR**
- Q.3**
- (a) Explain lexical and semantic expansion of macro with example. **07**
- (b) Explain with example expansion time sequencing symbols and expansion time variable. **07**
- Q.4**
- (a) Define forward references. How it can be solved using back-patching? Explain with example. **07**
- (b) List out the tasks performed by the analysis and synthesis phase of a “Simple Assembly Language” **07**

OR

- Q.4

(a)

Consider the following assembly program

07
- START 500

READ N

MOVER CREG, ZERO

BK READ A

MOVER AREG, A

COMP AREG, MAX

BC LE, NT

MOVEM AREG, MAX

NT ADD CREG, ONE

COMP CREG, N

BC LT, BK

PRINT MAX

STOP

N DS 1

A DS 1

ZERO DC '0'

ONE DC '1'

MAX DC '0'

END
- Instruction opcodes:

READ-09, MOVER-04,MOVEM-05, ADD-01,COMP-06, BC-07, PRINT-10,

STOP-00

Assembler directive codes: START 01, END-02

Register code: AREG-01, CREG-03
1. Identify task performed by above program.

2. Generate symbol table

3. Show intermediate code generated by above program
- (b)

Explain operand and register descriptor with example. Also give best evaluation order for arithmetic expression: $a+b*c+d*e\uparrow f$

07
- Q.5

(a)

Define static pointer. Find Register Requirement (RR) for the below given expression

07
- $f + (x + y) * ((a + b) / (c - d))$
- (b)

Prepare Symbol Table & Quadruple Table using Value Numbers method

07
- Stmt No

Statement

5

A = 29.3 * D

17

B=24.5

31

C=A*B +W

49

X=A*B + Y
- OR
- Q.5

(a)

Explain program relocation with example.

07
- (b)

Write a short note on MS-DOS Linker.

07
